A METHOD, APPARATUS AND SYSTEM FOR MULTIPLE SIGNAL TRANSMISSION, RECEPTION, AND RESTORATION

BACKGROUND OF THE INVENTION

The present invention relates to the field of radio-communication, and especially to the

5   transmission, reception and restoration of signals, using multiple transmitting and

receiving elements.

Radio communication links are used in many applications including but not limited to

telecommunication microwave trunks, wireless access for telephony, the Internet and

10   radio relays. The dynamic development of the Internet, cellular telephony and mobile

applications produces an ever increasing demand on the available resource which in these

applications can be the frequency spectrum. Transmitting more information over radio

links is considered as a desirable feature by many companies. The drive for increased

link capacity has led to the use of high order modulation such as 128 and 256 order

15   quadrature amplitude modulation. However, increasing the modulation order imposes

difficult requirements on many link components in terms of linearity, phase noise etc.

Therefore, there are practical limits to this approach.

Another approach utilizes link reuse to increase the capacity. Doubling the link capacity may be accomplished by the traditional approach of using two orthogonal (e.g. horizontal and vertical) polarizations of radio waves. The two polarizations can be made only approximately orthogonal, therefore a certain amount of "cross-talk" between signals may

5   be present, often necessitating cross-talk cancellers. With this approach the capacity increase does not exceed a factor of two.

Antenna spatial beamforming may be used to reduce the interference between users located at different azimuth directions and to increase the overall system throughput.

10   Since a beamformer differentiates between signal sources having different arrival angles, the beamformer is less suitable for point to point communication applications, where the signal arrives from one angle. That is, to obtain the benefits of beamforming systems, the original high speed data stream should be first demultiplexed into at least two lower speed data streams and then transmitted from more than one geographic location which

15   creates a number of concerns. Firstly, the data stream demultiplexing, and the subsequent distribution of the lower speed data streams may be costly and complicated, requiring additional hardware and wired or wireless links. Secondly, licensing and operating the system in different spatial corridors may also increase the cost and complexity of systems based on beamforming.

20

A known multiple antenna system with increased data capacity is described by G. J.

Foschini, in a "Layered Space-Time Architecture for Wireless Communication in a

Fading Environment When using Multi-Element Antennas," Bell Labs Tech. J., Autumn

1996, pp. 41-59. Foschini teaches that by using 8 antenna elements, the spectral capacity

5   may be as high as 42 bit/s/Hz.   The BLAST (Bell Labs Layered Space-Time) systems

embody the techniques described here in US patent 6,370,129 and US patent 6,380,910.

The BLAST system utilizes, and in fact relies, on different transfer functions between the

transmitting and receiving antenna pairs.   These transfer function differences are caused

by the different multipath reflections.   Restoring the specific signals for the BLAST

10   system is complicated, and the reliance of the system on multipath limits the range of

applications.   The restoring, or equivalently "deconvolving" of the individual data

signals involves estimation of channel parameters and application of some complex

mathematical manipulations (such as singular value decomposition) on a matrix

containing these parameters.   Similar to the beamforming systems discussed above,

15   demultiplexing and multiplexing the signal, with spatially distributed antennas, presents

difficulties and additional cost in situations where a single high capacity link is needed.

In addition, these techniques are not reliable when applied to "point to point" microwave

systems since they will not be subject to continuous multipath reflections.

Yet another technique is described in US patent 6,331,837 (the "Shattil" patent) disclosing an example of the principles of spatial interferometry multiplexing. The Shattil patent teaches a general deconvolving solution for two transmitting and two receiving antennas, and generalizes the solution for antenna arrays having more than two

5   components.   In contrast to our invention, US patent 6,331,837 relies on angular differences between the transmitters, when using receiver beam forming and between the receivers, when using transmitter beamforming.   This will provide the necessary differences in arrival angles and amplitude gain ratios used by Shattil.   This means that either the transmitting antennas, or the receiving antennas would be geographically

10   dispersed, raising the same concerns discussed with beamformers.   Also, the patent does not teach how to deal with the multipath situation especially for multipath components arriving from the same direction as the main signal component.

Therefore, it is desirable to have an increase of data throughput, beyond that possible with

15   polarization diversity or higher order modulation systems, for systems with transmitting and receiving antennas which are not geographically dispersed and one which is tolerant of, but does not rely on multipath reflections.

SUMMARY OF THE INVENTION

In order to overcome the limitations inherent in the prior art related to increase of communication channel information throughput, a novel approach to communication channel reuse is disclosed.

5

The present invention in one of its broad aspects, discloses an approach to transmit and receive information using electromagnetic radiation wherein at least two electromagnetic radiation signals are superimposed in space and frequency, the electromagnetic radiation is detected by at least one spatially distant receiver and the signals are subsequently

10 restored. Both the transmitting and receiving systems are each connected to a plurality of collocated transmitting or receiving antennas. As used herein the term "collocated" is defined as elements which are located in a geographically similar location, more preferably not exceeding several meters of separation and more preferably located on the same supporting structure.

15

A further object of the present invention is to provide a system for simultaneous transmission, reception and restoration of a plurality of individual signals superimposed in space and frequency, comprising a plurality of collocated transmitter antennas transmitting signals which reuse a common frequency band, a plurality of collocated

20 receiver antennas receiving signals which reuse a common frequency band, a set of filters

used to process the said received or transmitted signals, and at least one summing node

summing the signals processed by the said filters. The filters are designed in such a way

that the signals bearing the original transmitted information are restored and the

interference resulting from simultaneous transmission of a plurality of signals is cancelled

5   or at least significantly reduced.

A further object of the invention is to provide for a method for simultaneous

transmission, reception and restoration of a plurality of individual signals superimposed

in space and frequency, comprising transmitting and receiving a plurality of signals

10   where the transmitting antennas are collocated and the receiving antennas are collocated

and the said antennas reuse a common frequency band, applying a set of filters to the said

received or transmitted signals, and summing the signals processed by the said filters

restoring at least one original signal and reducing the interference resulting from the

simultaneous transmission of a plurality of signals.

15

A further object of the invention is to provide restorer implementations for use in a

system with simultaneous transmission of multiple radio signals superimposed in space

and frequency, the said apparatus comprising interface means to a plurality of collocated

receiver antennas processing signals which reuse a common frequency band, a set of

filters, which is used to filter the said received signals, and at least one summing node

which sums the signals produced by said filters restoring at least one original individual

signal and reducing the interference resulting from simultaneous transmission of a

plurality of signals.

5

Further, the invention provides for the optimization of the separation between collocated

transmitting antennas and between collocated receiving antennas, relative to the distance

between the transmitting and receiving antennas in the said transmitting and receiving

systems so that the restoration of the received desired signal results in a reduction, more

10   preferably cancellation of at least one interfering signal simultaneous with constructive

superposition of at least one desired signal.

Further provided is a disclosure wherein each original individual information bearing

signal is assigned to a single transmitting antenna and the said signal restoration is

15   performed in the receiving system.

More specifically, the invention includes a means to perform the entire signal restoration

at the carrier or an intermediate frequency.   This may include a means where the filters

used in the restorers may be reduced to simple phase shifters.

20

Alternatively, the invention includes a means to perform the signal restoration at baseband. This includes a means where the filters used in the restorers may be reduced to single tap complex multiplications which adjust the phase and amplitude of the received signals, but in general, multi-tap filters may be required.

5

More specifically the invention may include a means to adjust the attributes of the filters to accommodate changes in the propagation channels between transmitting and receiving antennas. The adjustments may be facilitated by addition, to at least one original information bearing signal, a training signal when other signals may be paused. In other

10 embodiments of the invention, a pilot tone signal is added to at least one original signal. In other embodiments, a spread spectrum signal is added to the information bearing signal.

The invention may also include a means to calculate the values of the adjustments and the

15 said means may use adaptive techniques. The disclosed means may enforce cancellation of additionally added signals, thereby canceling interferers. In other embodiments of the invention, the channel's propagation matrix is estimated, then, subsequently inverted and the inverted matrix elements are used as the attributes of the said set of filters. In other embodiments, the attributes are calculated so that the filters' responses are estimates of

the responses of the propagation channels between appropriate transmitting and receiving antenna pairs.

Further, the invention includes a means wherein the signal premixing is performed in the transmitting system, containing the filters modifying the original individual signals. Here the restoration process may be accomplished directly by the physical superposition of radio waves on the individual receiving antennas, which in this case act as the summing nodes. More specifically, an implementation with feedback from the receiving system to the transmitting system is disclosed, the said feedback used to adaptively adjust attributes of the said filters.

Further provided is a disclosure of a system implementation comprising a means of restoration of signals superimposed in space and frequency and other diversity means, including but not limited to one utilizing orthogonally polarized electromagnetic radiation.

The accompanying drawings, which are incorporated in and constitute a part of this specification, illustrate preferred embodiments of the method, system and apparatus according to the invention and, together with the description, serve to explain the principle of the invention.

9

BRIEF DESCRIPTION OF DRAWINGS

FIG. **1A** is a diagrammatic representation of a system, where signals are transmitted by collocated antennas, superimposed, and received by collocated antennas.

FIG. **1B** explains the designation of the distances between antenna transmitting/receiving pairs.

FIG. **2A** is an example of the phase relationships of the system's signals when the antennas are aligned.

FIG. **2B** is an example of the phase relationships of the system's signals when the antennas are not aligned.

FIG. **3** shows the block diagram of the preferred embodiment of the system containing a restorer.

FIG. **4A** shows an RF or IF implementation of phase shifting used in the restorer.

FIG. **4B** shows the baseband implementation of phase shifting used in the restorer.

FIG. **5** illustrates one example of the transmitted data signals and their pauses, used to facilitate restorer adjustment.

FIG. **6A** shows an embodiment of the restorer which uses the matrix generation and inversion technique.

FIG. **6B** shows an embodiment of the restorer which is based on cancellation of an

interfering signal measured during paused transmission.

FIG. **6C** shows an embodiment of the restorer which is based on propagation channel

estimation and cancellation of interfering signals based on these estimates.

5   FIG. **7** illustrates an example of transmitted data signals, including the added pilot tones,

facilitating restorer adjustment.

FIG. **8A** is an embodiment of a restorer which uses transmitted pilot tones and the matrix

generation and inversion technique.

FIG. **8B** is an embodiment of a restorer based on detection and minimization of a pilot

10   tone through feedback and adaptive filtering.

FIG. **9** illustrates one example of the transmitted data signals and their additive low level

spread spectrum components which are used to facilitate restorer adjustment.

FIG. **10A** shows an embodiment of the restorer using channel estimation facilitated

through addition of spread spectrum signals to the data signals.

15   FIG. **10B**   shows an embodiment of the restorer which uses spread spectrum signals

combined with the data signals and is based on detection and minimization of an

additive spread spectrum signal.

FIG. **11** is a diagrammatic representation of a system, where signals are transmitted by

three collocated antennas, superimposed, and received by 3 collocated antennas.

11

FIG. **12A** is an example of the phase relationships of the system's signals using pre-

mixing within the transmitter system when the antennas are aligned.

FIG. **12B** is an example of the phase relationships of the system's signals using pre-

mixing within the transmitter system when the antennas are not aligned.

5   FIG. **12C** shows a block diagram of a system using pre-mixing within the transmitter

system.

FIG. **13** shows a system with signal restorers combined with cross polarization

interference cancellers

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

10   As used herein, "radio signal" means any information bearing electromagnetic (EM)

radiation, propagating through space capable of being detected at some spatially distant

location. As used herein, an "antenna" means an element or set of elements used to

transmit or receive EM radiation. As used herein, a "pilot tone" signal means a

sinusoidal signal of audible or non-audible frequency. The term "phasor" means a

15   vector, with its amplitude and phase used to represent a signal's instantaneous amplitude

and phase. The term "RF" will be used to denote radio (or carrier) frequency and the

term "IF" will be used to denote an intermediate frequency. The term "baseband" will

be used to denote signals which have their carrier translated to zero frequency.

FIG. 1A illustrates a system with two transmitting and two receiving antennas where both the transmitting and receiving antennas are collocated. In the system, two signals **102a** and **102b** are simultaneously transmitted by antennas **101a** and **101b** using the same carrier frequency. The collocation of antennas allows the operator, while increasing the

5   data rate using the techniques disclosed herein, to use a single space corridor for the radio link minimizing the chance of interference with other users and simplifying the licensing process.   A transmitter system **100** contains the transmitter **106** providing radio signals **102a** and **102b** transmitted by antennas **101a** and **101b**.   In addition to components which are well known to those skilled in the art, including but not limited to modulators,

10   upconvertors and power amplifiers, the transmitter also contains components which facilitate the restorers' adjustment, as described later.   The receiver **107** is part of an overall receiver system **105**.   On this drawing all antennas are perfectly aligned, i.e. antenna locations form a perfect rectangle.   Although, for demonstration of the present invention, the system is illustrated with two antenna pairs, a plurality of antennas at each

15   of the transmitting and receiving systems may be used.   The signals **103a** and **103b** are received by two receiving antennas **104a** and **104b**.   The separation between the two transmitting (and the two receiving) antennas is designated as "d" and the distance between the transmitting and receiving sites is "D".

FIG. **1B** shows the geometry of the transmitter and receiver antennas in the ideal case.

D_{11} is defined as the distance from transmitting antenna **101a** to receiving antenna **104a**

and D_{22} is defined as the distance from transmitting antenna **101b** to receiving antenna

104b. These will be referred to, herein, as "direct paths". D_{12} is defined as the distance

5   from transmitting antenna **101a** to receiving antenna **104b** and D_{21} is defined as the

distance from transmitting antenna **101b** to receiving antenna **104a**. These will be

referred to, herein, as "cross paths".   In the case which is considered ideal, when the

length of the cross paths exceed the direct paths by approximately ¼ of a wavelength, the

transmitted signals can be optimally separated, as explained later.

10

FIG. **2A** shows the signals' phasor representations applicable for restoration of signals

received at the receiving antennas **104a** and **104b**. These phasor representations are

equivalents of the transmitted signals shown as **102a** and **102b** in FIG. **1A**.   It will be

assumed, for illustration purposes, that the phase shift caused by the transmission in the

15   direct paths is a multiple of 360^0. This does not have to be true, in practice, since only

the relative phases of the received signals need to be accounted for. The signal

transmitted from **101a** will be referred to as signal "A", and the signal transmitted from

101b will be referred to as signal "B".   Signals corresponding to the first restorer are

shown in **200a**, where "A" is the desired signal and "B" is the interfering signal. Signals

20   corresponding to a second restorer are shown in **200b,** where "A" is the interfering signal

14

and "B" is the desired signal. The phasors of the transmitted signals are shown in **201a** and **201b**. The single primed phasors " A' " and " B' " shown in **202a** and **202b** are the phasors of the received signals which result from transmission of signals "A" and "B", respectively, along the direct paths. The double primed quantities " A'' " and " B'' " also

5 shown in **202a** and **202b** are the phasors of the received signals which result from transmission of the signals "A" and "B" respectively, along the cross paths. Although individual phasors are shown, it will be understood by one skilled in the art that the phasor of the received signal is the superposition of the individual phasors. The phasors of the signals on the first antenna, **104a** are shown in **202a**, and for the second antenna,

10 **104b** are shown in **202b**. For the restorer illustrated in **200a**, the signals from the first antenna are summed with properly phase shifted versions of the signals from the second antenna. This is shown in **203a**, and the final result in **204a**. For the second restorer, the signals from the second antenna are summed with properly phase shifted versions of the signals from the first antenna. This is shown in **203b**, and the final result in **204b**.

15 Illustration of the restoration process will be aided by considering the angles of the relevant phasors. Considering the ideal case with the first restorer only, a signal following the cross paths will experience a signal delay by quarter of a wavelength or equivalently a -90^0 phase shift. The signal being received by **104a** will be the "A" signal, plus the "B" signal shifted in phase by -90^0. Similarly, the signal being received by

20 **104b** will be the "B" signal plus the "A" signal shifted in phase by -90^0. If the signal

15

from **104a** is added to the signal from **104b**, shifted by an additional $+90^0$ as shown in

203a, the result is a signal "A" of twice the original strength, with none of signal "B" as

shown in **204a**. In summary, the coincidence of cancellation of signal "B" with the

constructive superposition of the restored signal "A" is realized due to additional phase

5   shift of 90^0 in the crosspath, accomplished by optimizing the separation distance d in

relation to the distance between receiving and transmitting sites D.

While FIG. **2A** shows signals which are obtained when the antennas are perfectly aligned,

10   it would be much more common in practice to operate with a system undergoing some

antenna motion or exhibiting some other imperfection. FIG. **2B** illustrates a case where

the antennas are "misaligned", perhaps due to an antenna mast being deflected, for

example, due to wind. In this case, the extra propagation delay of the signals in the cross

paths cause the phase shift of the resulting signals to be different than 90^0. Even in this

15   case, the restorer may still perform very good cancellation of one signal and near

optimum constructive combining of another one. The signals corresponding to the first

restorer are shown in **250a**. Signals corresponding to a second restorer are shown in **250b**,

where "A" is the interfering signal and "B" is the desired signal. These references to

signals "A" and "B" and also to " A' " and " B' " and " A'' " and " B'' " are the same as

20   those used in the discussion accompanying FIG. **2A**. The phasors of the transmitted

16

signals are shown as **251a** and **251b**. The phasors of the signals on the first receiver antenna are shown in **252a**, and for the second receiver antenna are shown in **252b**. For the first restorer, the signals from the first receiver antenna are summed with properly phase shifted versions of the signals from the second receiver antenna. This is shown in

5   **253a**, and the final result in **254a**. For the second restorer, the signals from the second receiver antenna are summed with properly phase shifted versions of the signals from the first receiver antenna. This is shown in **253b**, and the final result in **254b**. In order to obtain effective signal restoration (i.e. good constructive superposition of restored signals when the undesired signal is canceled), it is required that a sum of the angles between

10   " B″ "and " A′ " and between " A″ "and " B′ " is maintained close to $\pm 180^0$. This "angle sum" depends on the separation between antennas at both ends of the link and on the distance between receiving and transmitting sites. The angle sum will be approximately preserved with a phase change of the individual carriers, an angular slant of the antennas as well as antenna vertical misalignment. This is why the proposed systems tolerate

15   antenna movements, changes to the propagation condition, frequency shift between carriers, carrier frequency jitters and other similar impediments.

From the above discussion, it follows that the restorer optimization condition requires that, for the ideal antenna alignment, the crosspath exceeds the direct path by odd

20   multiples of a quarter wavelength. To illustrate the importance of optimized distance

17

between the antennas a counter-example will be used. For example, if instead of the odd

multiple of a quarter wavelength distance difference, an even multiple were

implemented, the cancellation of the interfering signal would coincidentally cause

cancellation of the desired signal as well. While the separation distance should be taken

5   into consideration, it is not, in fact, too critical since the gain of the restored signal when

considered as a function of the separation distance, is only slowly changing, near the

optimum point.

A block diagram of the preferred embodiment of the communication system, containing

10   collocated multiple antennas, utilizing superimposed signals and containing restorers

which cancel interfering signals and recover the originally transmitted signals is shown in

FIG. **3**. The two data sources are shown as **300a** and **300b**. It will be recognized by one

skilled in the art, that it will be useful to include means to provide additional signals

which can be used by the receiver to facilitate calculation of the estimates **315a** and **315b**

15   of the two original data signals **300a** and **300b.** Therefore among other possibilities,

the transmitted signal may include pauses, pilot tone signals or spread spectrum signals.

Possible implementations of these will be discussed in the following paragraphs. The

transmitter **106** may include means to generate these additional signal components. The

described receiving system **105** will have the means to suitably receive, frequency shift

20   and filter the signals. These means are well known to one skilled in the art and are

represented by **301, 302, 303** and **304**. These are followed by restorers shown collectively

in **305, 306, 307, 308, 309, 310, 311** and **312**. The signals may then undergo additional

processing which is also familiar to one skilled in the art by blocks **313** and **314**; said

processing may include but is not limited to demodulation, equalization, error correction,

5   etc.   As part of the first restorer, the adaptive adjustment block **309** is fed by the outputs

of blocks **301** and **302** or from the output of the summing node **311**.   Only one of these

should be needed but both are shown in the diagram.   Similarly, for the second restorer,

the adaptive adjustment block **310** is fed by the outputs of blocks **303** and **304** or from the

output of the summing node **312.**   Only one of these should be needed but both are

10   shown in the diagram.   The functioning of the adaptive adjustment blocks **309** and **310**

will be detailed later.   To illustrate the general preferred embodiment of the receiver

system, it will suffice that, for the first restorer, the adaptive adjustment block will be

used to determine the attributes and performance of filters **305** and **306**. The filters, in

turn, will modify the signals received by the receiving antennas **104a** and **104b**, so that at

15   the output of the summing node **311**, being the final output of the first restorer, the first

restorer's interfering signal will be eliminated and the desired signal will be detected,

preferably enhanced. Similarly at the final output of the second restorer, shown

collectively as components **307, 308, 310** and **312**, the second restorer's interfering signal

will be eliminated and its desired signal will be detected, preferably enhanced. The

19

detailed functions of the blocks presented in this diagram will be fully discussed in the subsequent descriptions.

FIGS. 4 to 10, for illustrative simplicity, will show only one of the restorers. The

5   accompanying descriptions may easily be extended to apply to the other restorer(s). These figures represent more detailed implementations of the general embodiment shown in FIG. 3. The suitability of a particular implementation will depend on many considerations including, but not limited to propagation channel delay spread, the channel dynamics, overall system requirements and system architecture. The implementation

10   shown in FIG. 6C will be preferred in a multitude of situations, as it is capable of performing well with propagation channels having significant delay spreads, yet it is computationally simple and effective. However, the simpler cases will be described first.

In the most basic scenario, without effects caused by multipath propagation causing

15   propagation channel delay spread, and with all signals matched in amplitude, signal restoration may be accomplished by summing phase shifted received signals. That is, the restorers can be simply implemented with signal phase shifters (complex number rotations at baseband frequencies) and a signal summing node. The required rotation of signal phasors (phase shift) may be implemented either in RF (or IF), as shown in

20   FIG. 4A or in baseband, as shown in FIG. 4B. The discussion of both will follow.

In FIG. **4A**, **400** represents the restorer, which comprises phase shifters, implemented by **401** and **402**, and a means **403** to calculate the desired phase shift by analyzing the signals provided to or obtained from summing node **406**, as described later. In some situations,

5 such as for a static propagation channel with known geometry, the desired phase shift may be pre-calculated. This is followed by IF signal processing shown in **404** and **405**, which will be familiar to one skilled in the art, and finally by processing through summing node **406**, to produce the interference cancelled signal. The phase shift of the first signal, effected by **401**, is accomplished by a numerically controlled oscillator **408**

10 and a mixer **407**. Similarly, the phase shift of the second signal, effected by **402**, is accomplished by a numerically controlled oscillator **409** and a mixer **410**.

In FIG. **4B**, **450** represents a single restorer, which comprises phase shifters, implemented by **458** and **459**, and a means **403** to calculate the desired phase shift by analyzing the

15 signals provided to or obtained from the summing node **406**, as described later. In some situations such as for static propagation channels with known geometry, the desired phase shift may be pre-calculated. This is followed by a signal summing node **460**, to produce the interference cancelled baseband signal. Blocks **451, 452, 453, 454, 455,** represent the receiver functions of (quadrature) demodulation which are well known to one skilled in

20 the art. Blocks **456** and **457** represent analog to digital converters for both inphase and

quadrature signals. Blocks **458** and **459** represent complex multipliers, which shift the

signal's phases. Finally, the summing node **460** operates on complex numbers and

produces the interference cancelled baseband signal.

5   In slightly more complicated situations, when matching of signal amplitudes can not be

assured, but channels may still be represented by a single ray, it will be recognized that a

gain adjustment will be required in at least one arm of the restorer. Signal filtering may

be implemented either in RF or in baseband.

10   FIGS. **5** to **10** disclose implementations specifically adapted to perform well with

propagation channels which are time varying.

FIG. **5** shows the alternating pausing of the two transmitted signals. The purpose of the

pauses is to transmit single signals, a condition which will simplify the adjustment of the

15   restorers' parameters. The data signals are represented by **501** and **502**. The selection of

the length of the pauses, shown collectively as **503** and **504**, is a compromise between the

acceptance of additional overhead and the provision of signals which will allow for

correct operation of the receiver. In a dynamic environment, the pauses should be

frequent enough that the receiver can track the propagation channel changes. They

20   should also be of long enough duration that the propagation channels are estimated with

22

adequate accuracy. The use of these pauses is discussed in the descriptions accompanying FIG. **6A, 6B** and **6C**.

An implementation of a receiver used to obtain one of the restored signals, is shown in

5   FIG. **6A**. This implementation is especially useful when expected propagation channels exhibit only small amounts of time dispersion. For larger amounts, the structures shown in FIG. **6B** and FIG. **6C** are preferred. For this receiver, shown as **600**, signals received by antennas **104a** and **104b** are amplified and filtered by **301** and **302** according to methods known by one skilled in the art, and then filtered, frequency translated, and

10   analog to digital converted by **601** and **602**. The internal configuration of **601** and **602** is variable, but also familiar to one skilled in the art. The functions of **600** which are specific to this implementation of the restorer, comprise matrix generation and inversion performed by **603**, phase corrections performed by **458** and **459,** and summing performed by **460**. The matrix generated is a 2x2 matrix of complex numbers, each representing the

15   phase (and magnitude) of the propagation channel between one of the transmitter antennas and one of the receiver antennas. The matrix M, contains the following elements

$$M = \begin{bmatrix} C_{11} & C_{12} \\ C_{21} & C_{22} \end{bmatrix}$$

where, in the case of only small amounts of time dispersion, C_{11}, C_{12}, C_{21}, and C_{22} are

each complex numbers where C_{ij} is the baseband representation of the propagation

channel from transmitter antenna "j" to receiver antenna "i".

5 The coefficients of this matrix may be estimated by several techniques, but in one

embodiment, are estimated during the signal pauses in two steps. When the first input

signal is paused, during the periods shown as **503** in FIG. **5**, the elements in the second

column of the matrix M are estimated by single tap adaptive filters. When the second

input signal is paused, during the periods shown as **504** in FIG. **5**, the elements in the first

10 column of the matrix M are estimated by single tap adaptive filters. These adaptive

filters are well known in the art, but are also described, for the more general case of

multi-tap filters, in the discussion accompanying FIG. **6B** and FIG. **6C**. When elements

of the matrix M have been estimated, it remains to invert the matrix, and apply the

numbers within this inverse through the multiplications represented by **458** and **459**, and

15 the summation represented by **460**. Recall that only one of the two restorers is shown in

FIG. **6A**, and that the other two multiplications by the remaining elements of M^{-1} will

be accomplished in the other restorer.

FIG. **6B** shows another implementation of the parts of the receiver which are specific to

20 one of the restorers. For this receiver **630**, both signals received by antennas **104a** and

24

104b are processed by **301** and **302** according to methods well known by one skilled in the art, and then filtered, frequency translated, and analog to digital converted by **601** and **602**. The internal configuration of **601** and **602** is variable, but familiar to one skilled in the art. The functions of **630** which are specific to this implementation of the restorer

5 comprise the adaptive algorithm, implemented within **632**, the FIR (finite impulse response) filter **631** being controlled by the adaptive algorithm, and the summing node **460**. The adaptive algorithm **632** is activated during the pauses of the appropriate transmitted signal. During the period when all of the transmitted signals are paused, except for the interfering signal, which is to be cancelled, the adaptive algorithm **632** for

10 the first restorer is activated. This allows the restorer to adapt in such a way as to cancel the interfering (in this case, the second) signal. The adaptation would proceed according to algorithms which are familiar to those skilled in the art, such as the "LMS" (least mean square) or "RLS" (recursive least square) adaptive algorithms. The LMS algorithm, as it applies here, is included. The samples which are input to the FIR filter **631** are referred

15 to as x_n. The samples which are output from **601** are referred to as d_n, and the output of the summing node **460** is referred to as e_n. The following definitions are used to describe the algorithm. The sampling frequency would most likely be twice the symbol frequency, but could be some other multiple, as would be recognized by someone skilled in the art.

x_n = input to the FIR filter **631**,

20 d_n = output from the first RF - - > baseband / ADC converter **601**,

25

e_n = output from the summing node **460**,

W_n = the vector of coefficients of the FIR filter shown as **631**,

X_n = the vector of input samples of the FIR filter shown as **631**,

The superscript "H" used on a vector represents the commonly known vector operation of

5   complex conjugate transposition. The output from the summing node **460** is calculated as

$$e_n = d_n - W_n^H X_n$$

And the filter coefficients **631** are updated according to the commonly known LMS

algorithm

$$W_{n+1} = W_n + \mu \, e_n^* \, X_n.$$

10

FIG. **6C** shows another implementation of the part of the receiver which may be used to

obtain one of the restored signals. For this receiver shown as **660**, signals received by

antennas **104a** and **104b** are processed by **301** and **302** according to methods well known

by one skilled in the art, and then filtered, frequency translated, and analog to digital

15   converted by **601** and **602**. The internal configuration of **601** and **602** is variable, but

familiar to one skilled in the art. The functions of **660** which are specific to this

implementation of the restorer, comprise the adaptive algorithms, implemented by means

represented by **663** and **664**, the FIR filters **661** and **662** being controlled by the adaptive

algorithms **663** and **664**, and the summing node **460**.

During the period when all of the transmitted signals are paused, except for the interfering signal, which is to be cancelled, the adaptive algorithms **663** and **664** operating in the first restorer are activated. This allows the canceller to adapt in such a way as to cancel the

5   interfering (in this case, the second) signal. For illustrative purposes, these adaptive algorithms will take the form of channel estimators and are detailed in the following set of equations. Let the following samples be defined:

x_n^1 = output sample from **601**,

x_n^2 = output sample from **602**,

10   d_n = transmitted known signal samples (e.g. training pattern for second channel),

X_n^1 = set of input samples to FIR filter **661**,

X_n^2 = set of input samples to FIR filter **662**,

W_n^1 = set of filter coefficients of FIR filter **661** and

W_n^2 = set of filter coefficients of FIR filter **662.**

15   The prediction errors for the adaptive algorithms may be calculated as

$$e_n^1 = d_n - \left(W_n^1\right)^H X_n^1,$$

and

$$e_n^2 = d_n - \left(W_n^2\right)^H X_n^2.$$

And the coefficients of the adaptive filters are updated according to

27

$$W_{n+1}^1 = W_n^1 + \mu \left(e_n^1 \right)^* X_n^1$$

and

$$W_{n+1}^2 = W_n^2 + \mu \left(e_n^2 \right)^* X_n^2.$$

At the end of the adaptation, the coefficients of the FIR filters **661** and **662** are fixed for a

5   period of time, until another adaptation is required.

The following explanation of the cancellation occurring within the restorer serves to

illustrate the functions of the above equations. Considering only the signal transmitted by

the second transmitting antenna **101b**, recalling that the first signal has been paused (and

10   is therefore zero), the signals at the output of **601** and **602** have been subject to the

propagation channels C_{12} and C_{22} respectively. Assuming that these propagation

channels are accurately estimated, then the pair of received signals can be further filtered

by C_{22} and $-C_{12}$, respectively, resulting in similar signals which are then ideally cancelled

by summing node **460**. This has, in effect, cancelled the second signal, leaving only the

15   (filtered) first signal when the first signal is resumed. This is also illustrated by the

following equation where the input signal to the second channel is referred to as s_n^2, C_{12}

is the propagation channel from transmitter antenna **101b** to receiver antenna **104a**, C_{22} is

the propagation channel from transmitter antenna **101b** to receiver antenna **104b**, and

" ^ " denotes estimated quantities.

$$y_n = C_{12} * \hat{C}_{22} * s_n^2 \quad - \quad C_{22} * \hat{C}_{12} * s_n^2$$
$$\approx \quad 0.$$

This method of cancellation has two main advantages over methods which involve matrix inversion or channel transfer function inversion. Firstly, it tends to be numerically stable. Secondly, the FIR filters **661** and **662,** even with very few coefficients, form good

5   approximations of the impulse response of the propagation channels, leading to effective cancellation. Since only a few coefficients are required, high numerical efficiency of this implementation may be achieved.

FIG. **7** shows a pilot tone signal and its relationship to the data signals. In the present

10   invention, the purpose of the pilot tone signal is to provide the receiver with a reference which can be used to estimate the required filters attributes. The arrows separated by the symbol duration T are a representation of samples of the transmitted signals "A" and "B", and the low level pilot tone signal is shown as a sinusoid of period 2T, with a phase chosen so that the zero crossings of the sinusoid coincide with the data instants. The pilot

15   tone signal is alternately added to the first signal, shown as **701,** and then the second signal shown as **702.**

The main advantage of systems utilizing pilot signals is that interrupted transmission of the data signals is avoided. This allows for maximizing the data throughput in the link.

An apparatus with the pilot tone signal (analogous somewhat to the one described in FIG. 6A) is shown in FIG. **8A**. The signal receiver is shown in **800**. The invention specific components are pilot tone signal filters **801** and **802**, the channel estimator **803** and the matrix generator and inverter **804**. The channel estimator measures the relative phases and amplitudes of pilot tone signals in both propagation channels. Following this measurement, a matrix, representing the propagation channels is formed, by **804**, and inverted, providing multiplying coefficients for multipliers **458** and **459**.

Another implementation of the restorer **850** is shown in FIG. **8B**. Similar to the restorer shown in FIG. **6B**, feedback is used, by an adaptive algorithm **853**, in order to adjust the coefficients of filter **851**. A pilot tone signal detector **852** is used in the recovered signal during the time when the pilot tone signal is added to the interfering signal. Due to the adaptation and filtering, after a period of time, this recovered signal will not contain a significant amount of the pilot tone signal, and therefore, it may be expected that the signal restorer has successfully removed the transmitted signal which contained the pilot tone signal.

When the multipath time dispersion is large, the correction used in the restorer will usually require more than a single phase shift. Therefore implementations assisted by the

30

sinusoidal pilot tone should be used primarily for propagation channels with low delay spread.

The signals shown in FIG. **9** show low level spread spectrum signals **903** and **904** which

5   are added to each of the transmitted data bearing signals **901** and **902**. The receiver utilizes these spread spectrum signals in order to estimate the propagation channels. These estimates are then used in the restorers shown in FIG. **10A** and FIG. **10B**. Both implementations have the advantage of maximizing data throughput since the signal transmission is not paused and that they are applicable to propagation channels with

10   significant delay spread. It is worthwhile to note that, when the restorers are used to reconstruct spread spectrum signals, the codes for the original signals may be reused, so that the original signals may be superimposed in space, in frequency and in the code domain.

15   In FIG. **10A**, the components specific to the restorer implementation in the receiver **1000,** are the channel estimators based on the spread spectrum signals, shown as **1003** and **1004,** the FIR filters **1001** and **1002** and the summing node **460**. By supplying these channel estimators implemented as correlators, with the spreading code of the interfering signals and the factual received signals, the estimates of the propagation channels are

20   calculated and supplied to FIR filters **1001** and **1002**. After passing through FIR filters

1001 and **1002,** the interfering signals in both arms of the signal summing node **460** are approximately identical and will cancel one another as it was described in the explanation accompanying FIG. **6C.**

5   In FIG. **10B,** an apparatus using feedback is presented. The output of the restorer **1050** is analyzed for the presence of the added spread spectrum signal associated with the interfering signal. This function is performed by the analyzer **1053** which is supplied with the spreading code of the interfering signal for the reference. The adaptive algorithm **1052** supplies an optimized set of coefficients to the FIR filter **1051** to

10   minimize the magnitude of the signal detected, using an algorithm selected from those which are well known by those skilled in optimization theory.

   The implementations disclosed thus-far, may be extrapolated to situations where more than 2 antennas are used at each communication transmitter and receiver. FIG. 11

15   illustrates the case for 3 transmitting antennas **1101a, 1101b,** and **1101c** transmitting signals **1102a, 1102b,** and **1102c.** The 3 received signals are **1103a, 1103b,** and **1103c,** which are received by corresponding antennas **1104a, 1104b,** and **1104c.** Of course, systems with more than 3 antennas and, in fact, different spatial configurations of the multitude of antennas are quite possible. For the 3 antenna case, the data capacity of the

20   communication system is effectively tripled. In the described embodiment, the 3

transmitting antennas are configured as an equilateral triangle. Also, the 3 receiving

antennas are configured as a similar equilateral triangle. The transmitter **1100** will

usually contain means to demultiplex the high speed input data stream into 3 lower speed

data streams. Likewise, the receiver **1105** will usually contain means to multiplex the 3

5   lower speed received data streams into a single higher speed data stream. Similar to the 2

antenna case, the "direct paths" will be those associated with corresponding corners of the

triangle of transmitting antennas and the triangle of receiving antennas. "Cross paths" are

the other paths, and are slightly longer. In the implementation shown here, the separation

between corners of the two triangles is selected so that the delay associated with each

10   cross path causes a phase shift of approximately -120^0, relative to the phase shift caused

by the direct paths. The receiver techniques applicable for the two antenna case may be

extended to the 3 antenna case.

By way of example, a third antenna may be added to the structure shown in FIG. **6A**, and

15   the matrix generation and inversion technique may be applied with the following

modifications to the corresponding matrix, which now is of dimension 3x3. The matrix

of estimated channel propagation coefficients would, in the ideal case, be

$$M_3 = \begin{bmatrix} 1 & e^{-j\frac{2\pi}{3}} & e^{-j\frac{2\pi}{3}} \\ e^{-j\frac{2\pi}{3}} & 1 & e^{-j\frac{2\pi}{3}} \\ e^{-j\frac{2\pi}{3}} & e^{-j\frac{2\pi}{3}} & 1 \end{bmatrix}$$

33

The phases applied at the receiver are taken from the inverse of this matrix which is given by

$$
M_3^{-1} = \frac{1}{3}
\begin{bmatrix}
1 & e^{j\frac{2\pi}{3}} & e^{j\frac{2\pi}{3}} \\
e^{j\frac{2\pi}{3}} & 1 & e^{j\frac{2\pi}{3}} \\
e^{j\frac{2\pi}{3}} & e^{j\frac{2\pi}{3}} & 1
\end{bmatrix}
$$

5   While the embodiments described so far rely on separation of superimposed signals with most of the processing performed at the receiving system of a communication system, it is fully conceivable to move some of the restoration function to the transmitting system. To describe this implementation, we will use a simple system with two transmitting and two receiving antennas, separated in the same optimized way as the system with 2

10   transmitter and 2 receiver antenna discussed previously (i.e. in the ideal alignment case, the cross paths are a quarter of a wavelength longer than the direct paths). The phasors of the signals, for this case, are shown in FIG. 12A. The signals will again be referred to as "A" and "B". The subscript, either 1 or 2, will indicate which transmitting antenna the signal originated from, and single primes ("A'" or "B'") will indicate signals which have

15   propagated through a direct path and double primes ("A''" or "B''") will indicate a signal which has propagated through a cross path. The signal "A" will be considered to be the desired signal for the first restorer and the interfering signal for the second restorer. The signal "A" is shown to be transmitted with no phase change from 101a and a phase

advance of 90^0 from **101b**.   The signals corresponding to the first restorer are shown in

1200a and the second restorer in **1200b**. **1201a** shows the two phasors which make up

the first transmitted signal, and **1201b** show the two phasors which make up the second

transmitted signal.   The phasors of the received signals are shown in **1202a** and **1202b**.

5   The signals superimpose at the receiver antennas, giving the restored signals shown as

phasors in **1203a** and **1203b**.   The result of the design of this system is that the

interfering signals would destructively interfere and the desired signals would

constructively combine.

10   When the antenna alignment is changed, the phases between additionally injected signals

"B_1" and "A_2" needs to be adjusted, but so long as the advancement of additionally

injected signals adds up to 180^0 (sum of angle between signal phasors A1 and B1 and

angle between signal phasors B2 and A2), the cancellation of interfering signals and

optimum combining of the desired signal may be achieved.   An illustration of the phasor

15   orientation, for this case, at the transmitting and receiving ends of the system is shown in

FIG. **12B**. The signals corresponding to the first restorer are shown in **1250a** and the

second restorer in **1250b**. **1251a** shows the two phasors which make up the first

transmitted signal and **1251b** show the two phasors which make up the second

transmitted signal.   The phasors of the received signals are shown in **1252a** and **1252b**.

The signals superimpose at the receiver antennas, giving the phasors shown in **1253a** and **1253b**.

Premixing of the signals at the transmitting system is quite suitable for stationary systems,

5   when the advancement of the injected signals can be calculated and remains relatively

constant.   In general circumstances, e.g. non-negligible antenna motion, this method will

require a feedback link from the receiver, back to the transmitter, in order to update the

correct phase adjustments on the injected signals.   This method does not have to be

limited to the systems described above and may be extended to systems utilizing more

10   than two receiving and transmitting antennas.

FIG. **12C** shows a block diagram of a communication system which premixes the signals

at the transmitting end, and uses a feedback link from receiver to transmitter.   The

transmitting system, in addition to elements known to those skilled in the art include, but

15   are not limited to modulators, upconverters, power amplifiers and other components

shown collectively as TxF **1276** and **1277**, may contain filters H1 **1272** , H2 **1273**, H3

1274, and H4 **1275** as well as means **1270** and **1271** to control the filters attributes and

summing nodes **1283** and **1284**.   Also, a feedback means **1281** may be provided to

provide an "error" signal transmitted by the receiver subsystem **1282** and received by

20   **1280**.   This error signal is used to calculate the adjustments in the filters **1272, 1273,**

1274 and **1275**.   These filters may be simple phase shifters, or more complicated

adaptive filters as mentioned in the descriptions for FIGs. **6a** and **6b**.   The goal of these

adaptive algorithms may be to reduce the error signals which are transmitted on the

feedback link **1281**.   The receiver will contain, in addition to components well known to

5   those skilled in the art, include but are not limited to downconverters, LNAs, and mixers

shown collectively in **1278** and **1279**, an error extraction and processing means **1282**.

The error signal may be calculated with the aid of pauses in the transmitted signals, the

injection of pilot tone signals or the injection of low level spread spectrum signals.

10   FIG. **13** shows the restorers, described in this patent in combination with cross

polarization and optional cross polarization interference cancellers (XPICs).   One may

approximately double the data carrying capacity of a telecommunication's link by

exploiting the orthogonal polarizations of the signal, independently of the increase in

throughput obtained with the restorers.   The horizontal and vertical polarizations are

15   indicated here by the superscripts $^{\text{"HP"}}$ and $^{\text{"VP"}}$, respectively.   The components which

would be present without cross polarization signals are shown as input to the receiver

antennas **104a** and **104b**, and the restorers **1305a** and **1305b** which are shown as 2 of the

4 restorers **1305**.   The additional components in a system which utilizes cross

polarization are the vertically aligned antennas **1301a** and **1301b**, the Rx front ends, **1303**

20   and **1304**, additional restorers shown as **1305c** and **1305d**, and optionally, the XPICs

shown collectively as **1306**, comprised of individual XPICs **1306a, 1306b, 1306c,** and

1306d. In this figure, restorer **1305a** restores the horizontally polarized component of

the first transmitted signal and restorer **1305b** restores the horizontally polarized

component of the second transmitted signal. Similarly, restorer **1305c** restores the

5   vertically polarized component of the first transmitted signal and restorer **1305d** restores

the vertically polarized component of the second transmitted signal. As with any system

using cross polarization, there is often cross talk between the polarizations. For example,

an XPIC may be designed to operate on the horizontally polarized signal by removing

interference arising from the vertically polarized signal. In such a case, when the cross

10   polarization system is combined with the techniques presented in this disclosure, the

performance of an XPIC would be improved by including an input for the cross polarized

interfering signal, i.e. each XPIC would have 3 inputs. The restorers may make use of

any of the (suitably modified) techniques described previously. While this particular

embodiment illustrates a combination of the restorer with polarization diversity means,

15   one skilled in the art of communication may easily realize that any other diversity means

may be used instead of polarization diversity including but not limited to frequency

diversity, code diversity for spread spectrum signals, space diversity and time diversity.

Although the disclosure describes and illustrates preferred embodiments of the invention,

20   it is to be understood that the invention is not limited to these particular embodiments.

Many variations and modifications will now occur to those skilled in the art of radio

communications. For a definition of the invention, reference is to be had to the attached

claims.

5

10   We claim:

1. A communication system for simultaneous transmission, reception and restoration

   of a plurality of individual signals superimposed in space and frequency,

   comprising

   a plurality of collocated transmitter antennas transmitting signals which reuse a

15   common frequency band,

   a plurality of collocated receiver antennas receiving signals which reuse a

        common frequency band,

   a set of filters, having at least one filter, which is used to process the said

        received or transmitted signals, and